

## Simplify the Boolean Function using Karnaugh Map (K-Map)

The second method that used to simplify the Boolean function is the Karnaugh map. K-map basically deals with the technique of inserting the values of the output variable in cells within a rectangle or square grid according to a definite pattern. The number of cells in the K-map is determined by the number of input variables and is mathematically expressed as two raised to the power of the number of input variables, i.e.,  $2^n$ , where the number of input variables is  $n$ .

Thus, to simplify a logical expression with **two inputs**, we require a K-map with ( $2^2 = 4$ ) cells. A **four-input** logical expression would lead to a ( $2^4 = 16$ ) celled-K-map, and so on.

### Advantages of K-Maps

- 1- The K-map simplification technique is simpler and less error-prone compared to the method of solving the logical expressions using Boolean laws.
- 2- It prevents the need to remember each and every Boolean algebraic theorem.
- 3- It involves fewer steps than the algebraic minimization technique to arrive at a simplified expression.
- 4- K-map simplification technique always results in minimum expression if carried out properly.

### Disadvantages of K-Maps

- 1- As the number of variables in the logical expression increases, the K-map simplification process becomes complicated.
- 2- The minimum logical expression arrived by using the K-map simplification procedure may or may not be unique depending on the choices made while forming the groups

## K-mapping & Minimization Steps

Step 1: generate K-map based on the number of input variables  $n$

- Put a 1 in all specified minterms
- Put a 0 in all other boxes (optional)

Step 2: group all adjacent 1s without including any 0s. All groups must be rectangular and contain a “power-of-2” number of 1s 1, 2, 4, 8, 16, 32, ...

Step 3: define product terms using variables common to all minterms in group

Step 4: sum all essential groups plus a minimal set of remaining groups to obtain a minimum SOP.

### 1- Two variables K-Map

Number of input variables are 2

Hence the number of squares =  $2^n = 2^2 = 4$

Inputs A B		Decimal equivalent	Minterms	Output F
0	0	0	$m_0$ $\overline{A}\overline{B}$	
0	1	1	$m_1$ $\overline{A}B$	
1	0	2	$m_2$ $A\overline{B}$	
1	1	3	$m_3$ $AB$	

And K-Map of two variables is:

	$\overline{B}$	$B$
	0	1
$\overline{A}$	0	1
$A$	2	3

**Example:** simplify the Boolean expression by using K-Map

$$F = \bar{A}B + AB$$

**Solution:**

Number of input variables are 2

Hence the number of squares =  $2^n = 2^2 = 4$

	$\bar{B}$	$B$
	0	1
$\bar{A}$	0	1
$A$	0	1

A Karnaugh map for the expression  $F = \bar{A}B + AB$ . The map is a 2x2 grid. The columns are labeled  $\bar{B}$  (0) and  $B$  (1). The rows are labeled  $\bar{A}$  (0) and  $A$  (1). The cells contain values: top-left (0,0) is 0, top-right (0,1) is 1, bottom-left (1,0) is 0, and bottom-right (1,1) is 1. A blue circle groups the two 1s in the right column (minterms 1 and 3). Red numbers 0, 1, 2, and 3 are placed in the top-right, bottom-right, bottom-left, and top-left cells respectively.

$$F = B$$

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B) = \sum m(2, 0, 3)$$

**Solution:**

Number of input variables are 2

Hence the number of squares =  $2^n = 2^2 = 4$

	$\bar{B}$	$B$
	0	1
$\bar{A}$	1	0
$A$	1	1

A Karnaugh map for the expression  $F(A, B) = \sum m(2, 0, 3)$ . The map is a 2x2 grid. The columns are labeled  $\bar{B}$  (0) and  $B$  (1). The rows are labeled  $\bar{A}$  (0) and  $A$  (1). The cells contain values: top-left (0,0) is 1, top-right (0,1) is 0, bottom-left (1,0) is 1, and bottom-right (1,1) is 1. A blue circle groups the two 1s in the left column (minterms 0 and 2). An orange circle groups the two 1s in the bottom row (minterms 2 and 3). Red numbers 0, 1, 2, and 3 are placed in the top-right, bottom-right, bottom-left, and top-left cells respectively.

$$F(A, B) = \bar{B} + A$$

**Example:** simplify the Boolean expression by using K-Map

$$F = \bar{A}B + \bar{A}\bar{B}$$

**Solution:**

Number of input variables are 2

Hence the number of squares =  $2^n = 2^2 = 4$

	$\bar{B}$	$B$
	0	1
$\bar{A}$	0 1	1 1
$A$	2 0	3 0

$$F = \bar{A}$$

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B) = \sum m(0, 3)$$

**Solution:**

Number of input variables are 2

Hence the number of squares =  $2^n = 2^2 = 4$

	$\bar{B}$	$B$
	0	1
$\bar{A}$	0 1	1 0
$A$	2 0	3 1

$$F(A, B) = \sum m(0, 3) = \bar{A}\bar{B} + AB$$

## 2- Three Variables K-Map

Number of input variables are 3

Hence the number of squares =  $2^n = 2^3 = 8$

The truth table is

Inputs			Decimal equivalent	Minterms		Output F
A	B	C				
0	0	0	0	$m_0$	$\overline{A}\overline{B}\overline{C}$	
0	0	1	1	$m_1$	$\overline{A}\overline{B}C$	
0	1	0	2	$m_2$	$\overline{A}B\overline{C}$	
0	1	1	3	$m_3$	$\overline{A}BC$	
1	0	0	4	$m_4$	$A\overline{B}\overline{C}$	
1	0	1	5	$m_5$	$A\overline{B}C$	
1	1	0	6	$m_6$	$AB\overline{C}$	
1	1	1	7	$m_7$	$ABC$	

And the K-Map of three variables is:

	$\overline{B}\overline{C}$ 00	$\overline{B}C$ 01	$BC$ 11	$B\overline{C}$ 10
$\overline{A}$ 0	0	1	3	2
$A$ 1	4	5	7	6

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B, C) = \overline{A}\overline{B}\overline{C} + \overline{A}BC + \overline{A}B\overline{C}$$

**Solution:**

Number of input variables are 3

Hence the number of squares =  $2^n = 2^3 = 8$

	$\overline{B}\overline{C}$ 00	$\overline{B}C$ 01	$BC$ 11	$B\overline{C}$ 10
$\overline{A}$ 0	1 <sup>0</sup>	0 <sup>1</sup>	1 <sup>3</sup>	1 <sup>2</sup>
$A$ 1	0 <sup>4</sup>	0 <sup>5</sup>	0 <sup>7</sup>	0 <sup>6</sup>

$$F(A, B, C) = \overline{A}\overline{C} + \overline{A}B$$

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B, C) = \sum m(0, 3, 7, 6)$$

**Solution:**

Number of input variables are 3

Hence the number of squares =  $2^n = 2^3 = 8$

	$\overline{B}\overline{C}$ 00	$\overline{B}C$ 01	$BC$ 11	$B\overline{C}$ 10
$\overline{A}$ 0	1 <sup>0</sup>	0 <sup>1</sup>	1 <sup>3</sup>	0 <sup>2</sup>
$A$ 1	0 <sup>4</sup>	0 <sup>5</sup>	1 <sup>7</sup>	1 <sup>6</sup>

$$F(A, B, C) = \overline{A}\overline{B}\overline{C} + BC + AB$$

### 3- Four Variables K-map

Number of input variables are 4

Hence the number of squares =  $2^n = 2^4 = 16$

The truth table is

Inputs				Decimal equivalent	Minterms		Output F
A	B	C	D				
0	0	0	0	0	$m_0$	$\overline{A}\overline{B}\overline{C}\overline{D}$	
0	0	0	1	1	$m_1$	$\overline{A}\overline{B}\overline{C}D$	
0	0	1	0	2	$m_2$	$\overline{A}\overline{B}C\overline{D}$	
0	0	1	1	3	$m_3$	$\overline{A}\overline{B}CD$	
0	1	0	0	4	$m_4$	$\overline{A}B\overline{C}\overline{D}$	
0	1	0	1	5	$m_5$	$\overline{A}B\overline{C}D$	
0	1	1	0	6	$m_6$	$\overline{A}BC\overline{D}$	
0	1	1	1	7	$m_7$	$\overline{A}BCD$	
1	0	0	0	8	$m_8$	$A\overline{B}\overline{C}\overline{D}$	
1	0	0	1	9	$m_9$	$A\overline{B}\overline{C}D$	
1	0	1	0	10	$m_{10}$	$A\overline{B}C\overline{D}$	
1	0	1	1	11	$m_{11}$	$A\overline{B}CD$	
1	1	0	0	12	$m_{12}$	$AB\overline{C}\overline{D}$	
1	1	0	1	13	$m_{13}$	$AB\overline{C}D$	
1	1	1	0	14	$m_{14}$	$ABC\overline{D}$	
1	1	1	1	15	$m_{15}$	$ABCD$	

And the K-Map of four variables is:

	$\overline{C}\overline{D}$ 00	$\overline{C}D$ 01	$CD$ 11	$C\overline{D}$ 10
$\overline{A}\overline{B}$ 00	0	1	3	2
$\overline{A}B$ 01	4	5	7	6
$AB$ 11	12	13	15	14
$A\overline{B}$ 10	8	9	11	10

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B, C, D) = \bar{A}\bar{B}\bar{C}\bar{D} + \bar{A}\bar{B}C\bar{D} + A\bar{B}\bar{C}\bar{D} + A\bar{B}C\bar{D} + \bar{A}BCD + AB\bar{C}\bar{D}$$

**Solution:** Number of input variables are 4  
 Hence the number of squares =  $2^n = 2^4 = 16$

	$\bar{C}\bar{D}$ 00	$\bar{C}D$ 01	$CD$ 11	$C\bar{D}$ 10
$\bar{A}\bar{B}$ 00	0 1	1 0	3 0	2 1
$\bar{A}B$ 01	4 0	5 0	7 1	6 0
$AB$ 11	12 0	13 1	15 0	14 0
$A\bar{B}$ 10	8 1	9 0	11 0	10 1

$$F(A, B, C, D) = \bar{B}\bar{D} + \bar{A}BCD + AB\bar{C}\bar{D}$$

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B, C, D) = \sum m(0, 2, 4, 6, 12, 14, 15, 8, 10)$$

**Solution:** Number of input variables are 4  
 Hence the number of squares =  $2^n = 2^4 = 16$

	$\bar{C}\bar{D}$ 00	$\bar{C}D$ 01	$CD$ 11	$C\bar{D}$ 10
$\bar{A}\bar{B}$ 00	0 1	1 0	3 0	2 1
$\bar{A}B$ 01	4 1	5 0	7 0	6 1
$AB$ 11	12 1	13 0	15 1	14 1
$A\bar{B}$ 10	8 1	9 0	11 0	10 1

$$F(A, B, C, D) = \bar{D} + ABC$$



## K-Map with Don't Care Conditions

In certain cases some of the minterms may never occur or it may not matter what happens if they do

- In such cases we fill in the Karnaugh map with an X that meaning don't care
- When minimizing an X is like a "joker"
- X can be 0 or 1 - whatever helps best with the minimization

**Example:** simplify the Boolean expression by using K-Map

$$F(A, B, C, D) = \sum m(3, 7, 9, 11) + \sum d(1, 5, 12, 14)$$

**Solution:** Number of input variables are 4

Hence the number of squares =  $2^n = 2^4 = 16$

	$\bar{C}\bar{D}$ 00	$\bar{C}D$ 01	$CD$ 11	$C\bar{D}$ 10
$\bar{A}\bar{B}$ 00	0	X	1	0
$\bar{A}B$ 01	0	X	1	0
$AB$ 11	X	0	0	X
$A\bar{B}$ 10	0	1	1	0

$$F(A, B, C, D) = \bar{A}D + \bar{B}D$$